

OUTDOOR

STECH

SOLAR 3 Pieces LED light



User Manual

FEATURES

Bright 74 Leds Solar Lights Outdoor

The wireless solar motion lights outdoor come with 74 ultra bright LED beads, and PET laminated solar pannel with 20% conversion rate. The outdoor solar security light also comes with the 2200mAh rechargeable battery, 900LM, 6500K high brightness beam output.

Sensitive PIR & Adjustable Angle

When the sensor is activated, the outdoor solar security light will continue on for 30 seconds after no motion is detection. The motion detection range of the outdoor solar security light is 16-26 feet. The upgraded solar flood light has a wider angle of lighting. The three heads can be adjusted to different angles to meet your needs. The outdoor solar security light with motion sensor can detect up to 32 feet range of motion within a 120-degree angle.

Long Time Working Time

The outdoor solar security light has built-in lithium rechargeable battery (2200mAh) ensures full charge at low light and can last up to 30 hours for night use, at glare it can last 6 hours. The adjustable motion sensor lights will Auto on at night / Auto off at sunrise and can work for over 5,000 working hours.

IP65 Waterproof & Heatproof

The outdoor solar lights motion sensor holds up in any weather conditions. Ideal LED motion sensor outdoor light for a yard, patio, garage, porch, front door, gutters, entryway or side of a house.

Easy-to-Install & Warranty

Installation steps: Turn on the switch before installation for charge → Drill holes with the Anchors → Screw the mounting bracket → Slip the light onto the bracket.

OPERATING INSTRUCTIONS

First press: 100% brightness for 20 seconds after motion is detected and will turn off without motion.
Second press: 100% brightness for 20 seconds after motion is detected, then 10% brightness and the light stays on in the dark.
Third press: 20% brightness and stays on in the dark.
Fourth press: turns off the light.

SPECIFICATIONS

Size: 280(L)X105(W)X150(H)mm
Solar panel: 150(L)x86(W)x1.5(Thick)mm
Output: 900LM
Weight:434g
Battery: 2X18650(3.7V/2400MAH)
Runtime: 6-8 hours; Charging time: 4-6 hours
PIR detection distance: 3-5m
PIR detection angle: 120°
Beam angle: 360°
Solar panel: 5.5V/1.8W monocrystalline silicon

WARNING

ATTENTION: In any case, never look directly at the LED without eye protection.



WARNING: You should not dispose of this device with your household waste.

A selective collection system for this type of product is implemented by your local authorities. Please contact your local authorities to find out how and where collection takes place. These restrictions apply because electrical and electronic devices contain dangerous substances that have harmful effects on the environment or on human health and must be recycled.

This symbol indicates that electrical and electronic devices are collected selectively. The symbol shows a waste container crossed out with an X symbol.

STECH is distributed by CJ Global Inc.
All rights reserved. 2010 Maple Ave Fair Lawn NJ 07410

